



## 907

Stereo Power Amplifier (40 Watts per Channel)

---



The **907** is a high-performance power amplifier for line-level stereo audio signals. It accepts a balanced stereo audio signal on a terminal block connector and delivers 40 watts per channel into an 8Ω load.

### FEATURES

---

- High Efficiency - Class D operation.
- Controls - Volume control knob & mute button.
- Gain Control DIP-Switch.
- Mute and On Indicator LEDs.
- Compact MultiTOOLS® - Up to 4 units can be rack mounted side-by-side in a 1U rack space with the optional RK-1 universal rack adapter.

**TECHNICAL SPECIFICATIONS**

INPUT:	1 balanced stereo audio on a terminal block connector.
OUTPUT:	1 balanced stereo audio (speakers) on a terminal block connector.
OUTPUT POWER:	40 watts per channel into 8 $\Omega$ .
OUTPUT MUSIC POWER:	150W per channel into 8 $\Omega$ .
INPUT SENSITIVITY:	1.2Vrms.
AMPLIFIER TYPE:	Class D.
VOLTAGE GAIN:	20dB (x10).
BANDWIDTH (-3DB):	20kHz.
S/N RATIO:	60.2dB.
COUPLING:	DC.
AUDIO THD + NOISE:	1.9%.
AUDIO 2ND HARMONIC:	0.3%.
POWER CONSUMPTION:	24V DC, 5A.
INCLUDED ACCESSORIES:	Power supply.
OPTIONS:	RK-1 19" rack adapter.
PRODUCT DIMENSIONS:	10.68cm x 10.35cm x 4.36cm (4.20" x 4.07" x 1.72" ) W, D, H
PRODUCT WEIGHT:	0.3kg (0.7lbs) approx.
SHIPPING DIMENSIONS:	35.10cm x 21.20cm x 7.20cm (13.82" x 8.35" x 2.83" ) W, D, H
SHIPPING WEIGHT:	1.3kg (2.8lbs) approx.

