



RC-2C

2-button Control Keypad (US, EU, UK)



RC-2C is ideal for simple, convenient control of small spaces with serial and IR controlled devices such as projectors and displays.

FEATURES

- Back Lit & Label Capable Buttons - 2 tri-color, tactile feedback, backlit buttons.
- Custom Labeled, Removable Button Caps.
- RS-232 Control Port - Controls a device via serial control protocols.
- IR Control Port - Controls a device via IR control protocols.
- Program Control - Program configuration with Kramer K-Config software – supports up to 4 commands per macro and 4 toggling macros per button
- Keypad Lock-Out - Option for tampering prevention by locking and unlocking of the keypad buttons.
- Mounting - In-wall, in standard 1 gang US, EU or UK wall junction boxes.

TECHNICAL SPECIFICATIONS

PORTS:	1 RS-232 on a terminal block connector; 1 IR OUT on a terminal block connector.
POWER CONSUMPTION:	12V DC, 40mA.
INCLUDED ACCESSORIES:	Power supply, label set, screwdriver.
OPTIONS:	RRK-121WP 19" rack adapter.
PRODUCT DIMENSIONS:	8.00cm x 1.30cm x 8.00cm (3.15" x 0.51" x 3.15") W, D, H
PRODUCT WEIGHT:	0.1kg (0.1lbs) approx.
SHIPPING DIMENSIONS:	23.20cm x 13.60cm x 10.00cm (9.13" x 5.35" x 3.94") W, D, H
SHIPPING WEIGHT:	0.4kg (0.9lbs) approx.

CONFIGURATIONS

RC-2C/EU(W)-80	EU-size RC-2C, White Design Frame, PSU & Power cord, Label Set
RC-2C/EU(G)-80	EU-size RC-2C, Gray Design Frame, PSU & Power cord, Label Set
RC-2C/EU(W)-86	UK-size RC-2C, White Design Frame, PSU & Power cord, Label Set
RC-2C/EU(G)-86	UK-size RC-2C, Gray Design Frame, PSU & Power cord, Label Set
RC-2C/US(W)	US-size RC-2C, White Design Frame, PSU & Power cord, Label Set
RC-2C/JP(W)	US-size RC-2C, White Design Frame, PSU & Japan Power cord, Label Set
RC-2C/US(G)	US-size RC-2C, Gray Design Frame, PSU & Power cord, Label Set
RC-2C/JP(G)	US-size RC-2C, Gray Design Frame, PSU & Japan Power cord, Label Set

