



## RC-52A

6-button Control Keypad with Knob (US, EU, UK)

---



The RC-52A is ideal for simple, convenient control of small spaces with serial and IR controlled devices such as projectors and displays, and volume control of their multimedia devices.

### FEATURES

---

- **Back Lit & Label Capable Buttons** - 6 yellow-color, tactile feedback, backlit buttons.
- **Custom Labeled, Removable Button Caps.**
- **Analog Knob** - Controls volume adjustments via bi-directional rotating 10V-range knob.
- **RS-232 Control Port** - Controls a device via serial control protocols.
- **IR Control Port** - Controls a device via IR control protocols.
- **IR Sensor Port** - Learns commands from IR remotes.
- **Program Control** - Program configuration with Kramer K-Config software, supports up to 4 commands per macro and 4 toggling macros per button.
- **Keypad Lock-Out** - Option for tampering prevention by locking and unlocking of the keypad buttons.
- **USB Port** - To upload configuration files and power the device during configuration.
- **Mounting** - In-wall, in standard 2 gang US, EU or UK wall junction boxes.
- **Easy Installation** - Fits to standard in-wall boxes for simple and cost-reducing installation.

## TECHNICAL SPECIFICATIONS

PORTS:	1 RS-232 on a terminal block connector, 1 IR OUT on a terminal block connector, 1 IR IN sensor (for learning), 1 mini USB port for configuration upload.
POWER CONSUMPTION:	5V DC, 150mA.
INCLUDED ACCESSORIES:	Power supply, label set, screwdriver.
OPTIONS:	RK-121WP 19" rack adapter.
PRODUCT DIMENSIONS:	15.10cm x 2.10cm x 8.00cm (5.94" x 0.83" x 3.15" ) W, D, H
PRODUCT WEIGHT:	0.0kg (0.0lbs) approx.
SHIPPING DIMENSIONS:	23.20cm x 13.60cm x 10.00cm (9.13" x 5.35" x 3.94" ) W, D, H
SHIPPING WEIGHT:	0.5kg (1.1lbs) approx.

## CONFIGURATIONS

RC-52A/EU-86(W)	UK-size RC-52A, White Design Frame, PSU & Power cord, Label Set, Screwdriver
RC-52A/EU-86(G)	UK-size RC-52A, Gray Design Frame, PSU & Power cord, Label Set, Screwdriver
RC-52A/EU-86(B)	UK-size RC-52A, Black Design Frame, PSU & Power cord, Label Set, Screwdriver
RC-52A/EU-86(BAL)	UK-size RC-52A, Brushed-aluminum Design Frame, PSU & Power cord, Label Set, Screwdriver
RC-52A/EU-80(W)	EU-size RC-52A, White Design Frame, PSU & Power cord, Label Set, Screwdriver
RC-52A/EU-80(G)	EU-size RC-52A, Gray Design Frame, PSU & Power cord, Label Set, Screwdriver
RC-52A/EU-80(B)	EU-size RC-52A, Black Design Frame, PSU & Power cord, Label Set, Screwdriver
RC-52A/EU-80(BAL)	EU-size RC-52A, Brushed-aluminum Design Frame, PSU & Local Power cord, Label Set, Screwdriver
RC-52A/US(W)	US-size RC-52A, White Design Frame, PSU & Power cord, Label Set, Screwdriver
RC-52A/JP(W)	US-size RC-52A, White Design Frame, PSU & Japan Power cord, Label Set, Screwdriver
RC-52A/US(G)	US-size RC-52A, Gray Design Frame, PSU & Power cord, Label Set, Screwdriver
RC-52A/JP(G)	US-size RC-52A, Gray Design Frame, PSU & Japan Power cord, Label Set, Screwdriver
RC-52A/US(B)	US-size RC-52A, Black Design Frame, PSU & Power cord, Label Set, Screwdriver
RC-52A/JP(B)	US-size RC-52A, Black Design Frame, PSU & Japan Power cord, Label Set, Screwdriver
RC-52A/US(BAL)	US-size RC-52A, Brushed-aluminum Design Frame, PSU & Power cord, Label Set, Screwdriver
RC-52A/JP(BAL)	US-size RC-52A, Brushed-aluminum Design Frame, PSU & Japan Power cord, Label Set, Screwdriver