



VA-1VGAN

Computer Graphics Video EDID Emulator



The **VA-1VGAN** is an EDID emulator for computer graphics video signals. The unit can capture an EDID setting in non-volatile memory from the output allowing convenient and reliable connection to the source.

FEATURES

- Bandwidth - 1.8GHz.
- Control - Capture button.

TECHNICAL SPECIFICATIONS

INPUT:	1 XGA input on a 15-pin HD (F) connector.
OUTPUT:	1 XGA output on a 15-pin HD (F) connector.
MAX. OUTPUT LEVEL:	>2Vpp.
BANDWIDTH (-3DB):	1.8GHz.
DIFF. GAIN:	0.02%.
DIFF. PHASE:	0.02Deg.
K-FACTOR:	<0.05%.
S/N RATIO:	74dB @5MHz (unweighted: 66dB).
CONTROLS:	Button for EDID capture.
COUPLING:	DC, direct wiring between input and output.
POWER CONSUMPTION:	5V DC, 20mA.
INCLUDED ACCESSORIES:	Power supply.
OPTIONS:	RK-4PT 19" rack adapter.
PRODUCT DIMENSIONS:	6.22cm x 5.18cm x 2.44cm (2.45" x 2.04" x 0.96") W, D, H
PRODUCT WEIGHT:	0.1kg (0.2lbs) approx.
SHIPPING DIMENSIONS:	17.40cm x 12.00cm x 8.60cm (6.85" x 4.72" x 3.39") W, D, H
SHIPPING WEIGHT:	0.4kg (0.9lbs) approx.

